



Quick Setup Guide for Partner Portal:


Adding customers, configuring Bridge Channels for recording, groups, and users

Contents

- Logging into Partner Portal..... 3
- Adding Customers 4
- Adding Bridge to Customer’s Account..... 7
- Adding Cameras to Cloud 9
- Create Recording Schedule12
- Create a Camera Group.....14
- Adding Users16

Logging into Partner Portal

- Open a web browser and go to the following URL:
<https://partner.sgcloud.cloud/auth/login>.
- Enter your credentials provided by Speco and click the Login button.



Adding Customers


When logged in, click the 'Customers' tab.

The screenshot displays the VTElectronics dashboard for 'JT Electronics'. The left sidebar contains navigation options: Dashboard, Customers (highlighted with a red box), Activity Log, Billing History, Storage Calculator, and Account Settings. The main dashboard area features three summary cards: 'Total Customers' (2, 0% vs. previous month), 'Total Cameras' (8, -40% vs. previous month), and 'Total Video Storage Usage' (0 TB). Below these is a 'Customers in States' bar chart showing a single bar for 'New York' with a value of approximately 2.0. To the right, a 'New Customers' table lists two entries:


#	Customer Name	Customer Email Address
1	Speco	jtaylor@specotech.com
2	Justin Test	specocloudtest2@gmail.cc

A 'Secure Guard' logo is visible in the bottom left corner of the dashboard.

Click '+ Add Customer'



Enter customer's information and click 'Add Customer'




A confirmed message will display informing you that a registration e-mail has been sent to the customer. Click 'OK'.

The screenshot displays the 'Customers' management page in the JTELECTRONICS system. The interface includes a sidebar with navigation options: Dashboard, Customers, Activity Log, Billing History, Storage Calculator, and Account Settings. The main content area shows a table of customers with columns for #, Customer Name, Customer Email Address, Phone Number, Storage Plan, and Action. A modal dialog box is centered on the screen, displaying a green checkmark icon and the text 'Success! Customer has been Added successfully An email has been sent to the customer to set password.' with an 'OK' button. The bottom left corner features a 'Secure Guard' logo.


#	Customer Name	Customer Email Address	Phone Number	Storage Plan	Action
1	John Smith	jsmith@email.com	555-555-5555	100 TB (Active)	

Adding Bridge to Customer's Account


Click '>' to go to the Customer's configuration portal.




A new tab will open for the customer's configuration portal. Click '+ Add Bridge'.



Enter Bridge information found in the System Config page of your SGBRIDGE's web portal. Please refer to the SGBRIDGE Quick Setup Guide to learn more. Once entered, click 'Add Bridge'




The Bridge will be listed.




Adding Cameras to Cloud


After adding your Bridge, click 'Camera Management' and click '+ Add Camera'.




Click 'Next'



Select the Bridge you want to add channels from and click 'Next'.



Select the cameras you want to record to the cloud and click 'Next'.



Cameras will be listed. **Cameras must be configured to H.264. If any channels are displaying H.265, change them to H.264.**


The screenshot displays the 'Cameras' management page in the JTELECTRONICS system. The page header shows the user 'John Smith' and a '+ Add Camera' button. The main content area features a table of cameras with the following columns: #, Bridge Name, Camera Name, Stream Format, Serial Number, PTZ, Health Status, and Actions. Two cameras are listed, both with 'H264' in the Stream Format column, which is highlighted with a red box. The table data is as follows:

#	Bridge Name	Camera Name	Stream Format	Serial Number	PTZ	Health Status	Actions
01	John Smith Bridge	O4VT2	H264	SQC3VAU859VF42DD	No	Online	[Eye] [Pencil] [Trash]
02	John Smith Bridge	O2FRM	H264	SGCC9Q2BQXTFSOX	No	Online	[Eye] [Pencil] [Trash]


At the bottom of the table, there is a pagination control showing '10 / Page' and a 'Go' button. The left sidebar contains navigation options: Dashboard, Schedule Recording, Manage Devices, Camera Management (highlighted), Bridge Management, Group Management, User Management, Activity Log, Purchase History, and Storage Calculator. A 'Secure Guard' logo is located in the bottom left corner of the sidebar.

Create Recording Schedule

Click 'Schedule Recording' and then click '+Add Schedule Recording'.



Give the schedule a name and select cameras that are to follow the schedule.



Fill in the schedule boxes for the days of the week and time blocks. You can select from Continuous, Motion, or Continuous and Motion. Once completed, click 'Save Schedule

Dashboard

Schedule Recording

Manage Devices

Camera Management

Bridge Management

Group Management

User Management

Activity Log

Purchase History

Storage Calculator

Secure Guard

JTELECTRONICS

Schedule Recording Add Schedule

John Smith

Enable Schedule

Schedule Name: Recording Schedule

Select Camera: O2BFRM X O4VT2 X Search

Recording Type: Continuous Motion Continuous And Motion Clear

Sun Mon Tue Wed Thu Fri Sat

00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23

Save Schedule Cancel

Schedule will be listed showing information entered.

JTELECTRONICS

Schedule Recording

John Smith

+ Add Schedule

All Cameras All Days Search for schedule name Search


#	Schedule Name	Camera	Day Name	Time Duration	Status	Action
1	Recording Schedule	O4VT2, O2BFRM	Sunday, Monday, Tuesday, Wednesday, Thursday, Friday, Saturday	168 hr	Enable	

10 / Page < 1 > Go


Secure Guard

Create a Camera Group

Click 'Group Management' and click '+ Add Group'.



Enter a name for the group and select cameras.



Group will be listed.


The screenshot displays the 'Groups' management page in the JTELECTRONICS system. The page header includes the JTELECTRONICS logo, the user name 'John Smith', and an 'Add Group' button. A search bar is located below the header. The main content area features a table with the following data:

#	Group Name	Cameras	Users	Actions
01	John's Cameras	2	0	


The table is highlighted with a red border. Below the table, there is a pagination control showing '10 / Page' and '1' of 1 page, with a 'Go' button. The sidebar on the left contains navigation links for Dashboard, Schedule Recording, Manage Devices (with a sub-menu for Camera Management, Bridge Management, and Group Management), User Management, Activity Log, Purchase History, and Storage Calculator. A 'Secure Guard' logo is visible at the bottom of the sidebar.

Adding Users

Click 'User Management' and click '+ Add User'.



Enter user information, select camera group, and set privileges. Once completed, click 'Add User'



A confirmed message will display informing you that a registration e-mail has been sent to the user.

The screenshot displays the 'User Management' section of the JTELECTRONICS web application. The interface includes a sidebar with navigation options such as Dashboard, Schedule Recording, Manage Devices, Camera Management, Bridge Management, Group Management, User Management (highlighted), Activity Log, Purchase History, and Storage Calculator. The main content area shows a table with columns for #, User Name, Email Address, Phone Number, Group, and Actions. A single user entry is visible: ID 01, Name Jane Smith, Email janesmith@e-mail.com, and Phone Number 444-444-4444. A modal dialog box is centered on the screen, displaying a green checkmark icon and the text 'Success! User has been added successfully. Email containing password setup link has been sent to the user's email address.' with an 'OK' button. The top right of the page shows the user 'John Smith' and an '+ Add User' button. A 'Secure Guard' logo is visible in the bottom left corner of the sidebar.

#	User Name	Email Address	Phone Number	Group	Actions
01	Jane Smith	janesmith@e-mail.com	444-444-4444	-	