

Digital AM/FM Tuner with 30 presets and 1 Watt Output

PFA

Features

- 30 station presets
 - 18 FM presets (3 groups of 6)
 - 12 AM presets (2 groups of 6)
- Scan and seek functions
- Auto-store memory function
- Preset memory scan function
- Stereo line level out
- Adjustable mono output up to 1W power for a standalone Music-on-hold system
- Signal strength indicator
- Rack mount kit included
- AM/FM antenna included
- Connection for 12/24V Battery Backup
- Standard 1 RU rack chassis



rear of unit

Specifications

Tuning Range	AM: 530kHz ~1620kHz FM: 87.5MHz ~ 108.0 MHz
Antenna Input	AM: Single conductor lead wire FM: 300 Ohms twin lead or 75 Ohms coax
Usable Sensitivity	AM: 4.5uV FM: 2uV
Signal to Noise Ratio.....	AM: 50dB FM: 60dB
Output Levels	Line: 775mV (0dBm) Unbalanced Music-on-hold: 775mV (0dBm) Balanced
Station Memory Backup ...	45 days (after AC power turned off)
Power Source	15W
THD	Less than 1% @1KHz
Signal/Noise Ratio	Microphone: >60dB / TEL: >60dB / Line: >70 dB
Controls	Power, Volume, Tuner (controls and presets)
Telephone	MoH Out
Indicators	Power, power level, tuner LCD
Includes	Rack-mount hardware
Dimensions.....	16.5" (W) x 1.7" (H) x 8.3" (D)
Weight	7.1 Lbs.

NDAA
COMPLIANT

*Products are in compliance with NDAA Section 889 Part B Guidelines

Speco Technologies is constantly developing and improving products.
We reserve the right to modify product design and specifications without notice
and without incurring any obligation. Spec Rev. 2/24/22